

	30A
	60V
	30mΩ
	40mΩ






SOT-89


Marking Code	

- Lead free product is acquired
- High density cell design for ultra low RDS(on)
- Good stability and uniformity with high EAS
- Power Management
- Excellent package for good heat dissipation
- Power switching application
- Hard switching and high frequency circuits
- Uninterruptible power supply

Drain-Source Voltage			60	
Gate-Source Voltage			20	
Continuous Drain Current	TA=25		30	
	TA=100		18	
Pulsed Drain Current (Note 1)			114	
Single Pulse Avalanche Energy (Note 2)			25.5	
Power Dissipation			34.7	
Junction Temperature			-55-+150	
Storage Temperature			-55-+150	
Thermal Resistance From Junction to Ambient (note 3)			3.6	

Drain-Source Breakdown Voltage	V_{GS}=0V, I_D=250uA		60			
Drain-Source Leakage Current	V_{DS}=48V, V_{GS}=0V TJ=25				1	
	V_{DS}=48V, V_{GS}=0V TJ=55				5	
Gate-body Leakage	V_{DS}=±20V, V_{DS}=0V				±100	
Drain-Source On-Resistance (note 4)	V_{GS}=10V, I_D=15A			21	30	
	V_{GS}=4.5V, I_D=10A			28	40	
Gate-Threshold voltage	V_{DS}=VGS, I_D=250uA		1.2	1.6	2.5	
Diode forward voltage	I_S=1A, V_{GS}=0V				1.2	
Forward Transconductance	VDS=5V,ID=15A			17		
Gate Resistance	VDS=0V,VGS=0V,f=1MHz			3.2		
Input capacitance	V_{DS}=15V, V_{GS}=0V, f=1MHz			1378		
Output capacitance				86		
Reverse Transfer capacitance				64		
Total Gate Charge	V_{GS}=4.5V V_{DS}=48V I_D=12A			12.6		
Gate Source Charge				3.2		
Gate Drain(Miller) Charge				6.3		
Turn-on Time	V_{GS}=10V I_D=10A V_{DD}=30V R_{GEN}=3.3Ω			8		
Rise time				14.2		
Turn-off Time				24.4		
Fall time				4.6		
Continuous Source Current	VGS=VDS=OV,Force Current				23	
Pulsed Source Current					46	









Fig.6 Normalized R_{DSON} v.s T_J

Fig.5 Normalized $V_{GS(th)}$ v.s T_J



tance

Fig.8 Safe Op ng Area

Fig.7 Capac




Fig.9 Normalized Maximum Transi nal Impedance




Fig.11 ductive Waveforn

		””r1	0”

The information presented in this document is for reference only. GuangDong Youfeng Microelectronics Co.,Ltd. reserves the right to make changes without notice for the specification of the products displayed herein to improve reliability, function or design or otherwise. The product listed herein is designed to be used with ordinary electronic equipment or devices, and not designed to be used with equipment or devices which require high level of reliability and the malfunction of with would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices),YFW or anyone on its behalf, assumes no responsibility or liability for any damages resulting from such improper use of sale. This publication supersedes & replaces all information previously supplied. For additional information, please visit our website https://www.yfwdiode.com, or consult YFW sales office for further assistance.